



Uniden Australia Pty Ltd

73 Alfred Road  
Chipping Norton 2170 NSW  
Tel: 02 9599 3355 | Fax: 02 9599 4018  
www.uniden.com.au

**UBC93XLT****Programmable Handheld  
200 Channel Scanner**

PRINT this page

EMAIL a friend

Range Brochure PDF

Operating Manual PDF

Like 78K

This handheld scanner with full frequency display offers 200 programmable memory channels - 8 bands. Offering the new Ground Breaking Technology "Close Call RF Capture Technology" this scanner automatically 'Listens' for any nearby or 'close' transmissions and once they occur the scanner immediately tunes in to this frequency which is ideal for use at events or locations when the transmission is unknown.

Frequency ranges received are 25-88, 108-174, 400-512 and 806-956 MHz. Chain searching allows seven different personal search bands and the ability to search up to all five chain locations at once. Priority scanning allows a designated priority channel to be monitored every two seconds.

The UBC93XLT also has Pre-Programmed service search which automatically detects analogue Police, Railroad, Air, Marine, UHF CB and AM CB channels.

The UBC93XLT comes with some great accessories including a Scanner Frequency CD, Earpiece Microphone and Cigarette Lighter Charger, AC Adaptor and 2 X NiMH Batteries.

Suggested Retail: \$269.95

**CLOSE CALL™**  
RF CAPTURE TECHNOLOGY

INCLUDES  
**800MHz**  
FREQUENCIES

CLICK HERE FOR

**UHF**  
Range Overview

**Key Features**

Designed and Engineered in Japan

200 Analogue Channels

8 Bands

Ultra Compact Design

Frequency Range: 25-88MHz, 108 □ 174 MHz, 400-512 MHz, 806-956 MHz

Close Call RF Capture Technology

Frequency Searching:

- Program Search
- Chain Search
- Direct Entry Search
- Analogue Pre Programmed Service Search\*:

- > Police
- > Railroadbr /> > Air
- > Marine
- > UHF CB
- > AM CB

- Frequency Skip

Channel Scanning:

- Memory Channel Scan
  - > Direct Channel Access
  - > Channel Lockout
  - > Priority Scan

TOP

:: Uniden Australia ::

- Duplicate Channel Alert

Backlit LCD Display

Keypad Lock

Key Touch Tone

Memory Back Up

Low Battery Alert

Includes 1 X AC Adaptor and 2 X Ni-MH Rechargeable Batteries

Additional Features:

External Jacks  ANT: BNC Type

Internal Speaker: 8ohm.1W

Max Search Speed: 150 Steps/sec

Operating Temperature: -20A - +60Ac

Size of Unit (mm): 68(w) x 31.5(D) x 115 (H)

Weight without battery: 165g

\*Please note not all pre-programmed service searches may operate in New Zealand.

[TOP](#) 